

MONSTER #1982 347

Listing of: (memory data)

Channel Group: Corrected Torque and Power Page 1 of 1

Printed on May 7, 2014 at 9:08:08

Test Description: Unused Test

|                              | EngSpd<br>RPM | STPTrq<br>Clb-ft | STPPwr<br>CHp | Fuel A<br>lb/hr | Air 1<br>scfm | A/F<br>Ratio | Oil P<br>psig | BSFC<br>lb/hph | OilOut<br>degF |
|------------------------------|---------------|------------------|---------------|-----------------|---------------|--------------|---------------|----------------|----------------|
| **                           | 4500          | 455.4            | 390.2         | 195.8           | 0             | 0.00         | 69.9          | 0.513          | 72             |
|                              | 4600          | 459.8            | 402.7         | 201.6           | 0             | 0.00         | 70.0          | 0.511          | 71             |
|                              | 4700          | 463.6            | 414.8         | 211.7           | 0             | 0.00         | 70.2          | 0.521          | 71             |
|                              | 4800          | 468.1            | 427.8         | 216.4           | 0             | 0.00         | 70.6          | 0.517          | 71             |
|                              | 4900          | 467.2            | 435.8         | 219.9           | 0             | 0.00         | 70.8          | 0.515          | 71             |
|                              | 5000          | 465.9            | 443.5         | 214.6           | 0             | 0.00         | 71.2          | 0.494          | 71             |
|                              | 5100          | 465.9            | 452.4         | 220.2           | 0             | 0.00         | 71.8          | 0.498          | 72             |
|                              | 5200          | 464.2            | 459.6         | 237.4           | 0             | 0.00         | 72.1          | 0.528          | 72             |
|                              | 5300          | 459.6            | 463.8         | 238.4           | 0             | 0.00         | 72.6          | 0.525          | 72             |
|                              | 5400          | 453.8            | 466.6         | 225.9           | 0             | 0.00         | 73.2          | 0.495          | 72             |
|                              | 5500          | 450.5            | 471.8         | 218.0           | 0             | 0.00         | 73.9          | 0.472          | 72             |
|                              | 5600          | 443.9            | 473.3         | 234.4           | 0             | 0.00         | 74.4          | 0.506          | 72             |
|                              | 5700          | 440.7            | 478.2         | 233.2           | 0             | 0.00         | 74.8          | 0.498          | 72             |
|                              | 5800          | 434.8            | 480.1         | 239.3           | 0             | 0.00         | 75.2          | 0.510          | 72             |
|                              | 5900          | 429.5            | 482.5         | 245.3           | 0             | 0.00         | 75.7          | 0.520          | 72             |
|                              | 6000          | 428.1            | 489.1         | 251.7           | 0             | 0.00         | 76.2          | 0.526          | 72             |
| **                           | 6100          | 426.3            | 495.1         | 257.6           | 0             | 0.00         | 76.6          | 0.532          | 72             |
|                              | 6200          | 420.2            | 496.0         | 247.1           | 0             | 0.00         | 77.1          | 0.509          | 72             |
|                              | 6300          | 417.0            | 500.2         | 253.3           | 0             | 0.00         | 77.5          | 0.518          | 72             |
|                              | 6400          | 411.2            | 501.1         | 253.5           | 0             | 0.00         | 77.9          | 0.517          | 72             |
|                              | 6500          | 406.0            | 502.5         | 257.2           | 0             | 0.00         | 78.1          | 0.524          | 71             |
|                              | 6600          | 397.8            | 499.9         | 261.3           | 0             | 0.00         | 78.7          | 0.535          | 71             |
| **Range: 4500 RPM - 6100 RPM |               |                  |               |                 |               |              |               |                |                |
| AVG:                         | 5300          | 451.6            | 454.5         | 227.1           | 0             | 0.00         | 72.9          | 0.511          | 72             |
| MIN:                         | 4500          | 426.3            | 390.2         | 195.8           | 0             | 0.00         | 69.9          | 0.472          | 71             |
| MAX:                         | 6100          | 468.1            | 495.1         | 257.6           | 0             | 0.00         | 76.6          | 0.532          | 72             |